

# Prestec SX Fire Panels



## ELECTRICAL SPECIFICATION

Mains Voltage	230VAC @ 50/60HZ
System Voltage	24VDC (Nominal)
Zone Voltage	21VDC (Nominal)
Sounder Alarm O/P	2x400mA @ 24VDC
Fault Relay Output	1xRelay SELV (1A)
Fire Relay Output	1xRelay SELV (1A)
Zone Capacity	32 Devices per zone
Remote Sounder Activation	Via N/O Contact
Sounder Activation Delay	0-9Minutes
Zone End Of Line	Diode (provided)
Sounder End Of Line	10K Resistor
Charger Voltage	27.6V open circuit
Charger Size	1500mAh
Zone Short Circuit Protection	100mA
Charger Short Circuit Protection	Batteries less 20V
Enclosure Size	355 x 275 x 100

The Prestec range of control panels is available in 1,2,4,6 & 8 zones, housed in light grey flame retardant ULV0 enclosure designed to meet modern architectural surrounding with a removable hinge door. The Prestec panel has been designed with ease of installation in mind in addition to the robust electronics.

## ORDER CODES

1 Zone Panel c/w Batteries	FP1
2 Zone Panel c/w Batteries	FP2
4 Zone Panel c/w Batteries	FP4
6 Zone Panel c/w Batteries	FP6
8 Zone Panel c/w Batteries	FP8



Tel. +44 1204 575100  
Fax. +44 1204 574100

email : [sales@saturnlighting.co.uk](mailto:sales@saturnlighting.co.uk)  
<http://www.saturnlighting.co.uk>